

# 20V 1/4 HEX TRANSDUCER SCREWDRIVER RRI-BCP16H2

RED ROOSTER Cordless transducerized screwdriver. Very well suited for assembly applications where good torque accuracy is required. 8 programs can be set for both torque and angular displacement. The programs can be easily selected or programmed in a fixed sequence. Contactless trigger and forward / reverse switch for a long lifetime. Repeatability Cm/Cmk > 2 at +/- 7%.

**Characteristics:**

- Brushless motor
- 20 Volt Lithium-Ion battery
- LED status indicates OK - NOK - REVERSE - BATTERY LOW
- Tightening mode setting – Torque or Angle
- Programmable torque
- Programmable angle limits
- Programmable speed
- Group check / counting
- 8 programs including sequence
- Compact and light weight
- The flat battery pack offers stability
- Battery (2,5 Ah: BB200D-325; 5,0 Ah: BB200D-350) and charger (B84192B) to be ordered separately

**Related products**



- BB200D-325  
20V 2.5Ah Battery, Li-ion
- BB200D-350  
20V 5.0Ah Battery, Li-ion
- B84192B  
18-20V Charger

**Related accessories**



- D39SC180B-1  
Suspension Bail



- 33116-B200D-01  
Protection Cover

- 766-027-612  
Side handle for BCP



- 61022-TH005  
Tool Holder



- 32088-NPA-01  
Cable



- 33116-B200D-02  
Protection Cover



- 61022-TH003  
Tool Holder, diameter 58mm

- 33116-NPA-01  
Protection Cover RRI-BCP



**Specifications**

Brand	RedRoosterIndustrial
Bolt capacity (mm)	6
RPM	100 - 500
Torque (Nm)	5 - 16
Weight w/o battery (kg)	1,01
Hexagon	1/4"
mm A	202,5
mm B	240,5
Battery voltage (Volt)	20
Battery type Li-ion....(Ah)	2,5 / 5,0
Safety standard	EN ISO 11148-6
Sound standard	ISO 15744
Sound pressure (dB(A))	< 75
Sound uncertainty (dB(A))	3
EAN	8717981418664

