

# 18V 1/4 HEX TRANSDUCERIZED SCREWDRIVER

## RRI-BCP08H2

RED ROOSTER Cordless transducerized screwdriver. Very well suited for assembly applications where good torque accuracy is required. 8 programs can be set for both torque and angular displacement. The programs can be easily selected or programmed in a fixed sequence. Contactless trigger and forward / reverse switch for a long lifetime. Repeatability Cm/Cmk > 2 at +/- 7%.

### Characteristics:

- Brushless motor
- 18 Volt Lithium-Ion battery
- LED status indicates OK - NOK - REVERSE - BATTERY LOW
- Tightening mode setting – Torque or Angle
- Programmable torque
- Programmable angle limits
- Programmable speed
- Group check / counting
- 8 programs including sequence
- Compact and light weight
- The flat battery pack offers stability
- Battery (2,5 Ah: BB200D-325; 5,0 Ah: BB200D-350) and charger (B84192B) to be ordered separately

### Related products

-  **BB200D-325**  
18V 2.5Ah Battery, Li-ion
-  **BB200D-350**  
18V 5.0Ah Battery, Li-ion
-  **B84192B**  
18-20V Charger

### Related accessories

-  **D39SC180B-1**  
Suspension Bail
-  **33116-B200D-01**  
Protection Cover
- 766-027-612**  
Side handle for BCP
-  **61022-TH005**  
Tool Holder
-  **32088-NPA-01**  
Cable
-  **33116-B200D-02**  
Protection Cover
-  **61022-TH003**  
Tool Holder, diameter 58mm
- 33116-NPA-01**  
Protection Cover RRI-BCP



### Specifications

Brand	RedRoosterIndustrial
Bolt capacity (mm)	5
RPM	220 - 1100
Torque (Nm)	3 - 8
Weight w/o battery (kg)	1,01
Hexagon	1/4"
mm A	202,5
mm B	240,5
Battery voltage (Volt)	18
Battery type Li-ion....(Ah)	2,5 / 5,0
Safety standard	EN ISO 11148-6
Sound standard	ISO 15744
Sound pressure (dB(A))	< 75
Sound uncertainty (dB(A))	3
EAN	8717981418640

