

18V SCREWDRIVER 1/4 HEX SHUT-OFF WLAN 3NM RRI-BSW3H2

RED ROOSTER Cordless shut-off screwdriver. Very well suited for assembly applications with a need of good torque accuracy. Especially in areas where cables and hoses impede handling flexibility, such as interiors of cars, coaches and trains. Contactless trigger and forward / reverse switch for a long lifetime.

Characteristics:

- Brushless motor
- 18 Volt Lithium-Ion battery
- LED status indicates OK - NOK - REVERSE - BATTERY LOW
- Adjustable torque
- Speed adjustable with programmer
- Compact and light weight

Battery (2,5 Ah: BB200D-325; 5,0 Ah: BB200D-350) and charger (B84192B) to be ordered separately

Related products

-  **DWL-B**
2.4G/5.8G WLAN receiver
-  **BB200D-325**
18V 2.5Ah Battery, Li-ion
-  **B74SC180B**
Programmer
-  **BB200D-350**
18V 5.0Ah Battery, Li-ion
-  **B84192B**
18-20V Charger

Related accessories

-  **D39SC180B-1**
Suspension Bail
-  **33154-SCEP-04**
Lock Nut Yellow
-  **61022-TH005**
Tool Holder
-  **33154-SCEP-03**
Lock Nut Blue
-  **61022-TH003**
Tool Holder, diameter 58mm
-  **D54SC#BV**
Lock Nut Black
-  **33116-SCEP-01**
Protection Cover
-  **00-4507**
Torque Adjust Key RRI screwdriver
-  **33154-SCEP-02**
Lock Nut Red



Specifications

Brand	RedRoosterIndustrial
Bolt capacity (mm)	4
RPM	200 - 500
Torque (Nm)	0,8 - 3
Weight w/o battery (kg)	1,0
Hexagon	1/4"
mm A	203
mm B	238
Battery voltage (Volt)	18
Battery type Li-ion....(Ah)	2,5 / 5,0
Safety standard	N ISO 11148-6
Vibration standard	EN ISO 28927-2
Vibration value (m/s ²)	0,1
Vibration uncertainty (m/s ²)	1,5
Sound standard	ISO 15744
Sound pressure (dB(A))	57,4
Sound uncertainty (dB(A))	3
EAN	8717981452743

